



### ART1/G2 Hands-Free Intercom Station (G2+ System)



#### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The hands-free type G2+ series intercom station(s) shall be Alpha Communications® / Golmar ART1/G2, or approved equal.

Station(s) shall be surface mounted on the wall (or desk mounted using optional #SOB-UNI desk adapter). Station(s) shall be connected using a simple 2-conductor non-polarized (loop) wiring. Station(s) shall feature electret condenser microphone for exceptional half-duplex digital voice fidelity. Station shall feature an electronic calling signal (selectable) and shall only protrude from the finished wall 0.59" inches (20mm). Station(s) shall feature 'braille' type dots for Talk and Door release functions, for visually impaired individuals.

Contractor shall observe all local and national electrical and building codes.

#### ART1/G2 HANDS-FREE INTERCOM STATION (G2+ SYSTEM)

The Alpha Communications® ART1/G2 G2+ series hands free type intercom stations use the G2+ technology to provide the most advanced intercom system available, for any multi-unit building up to 4,096 apartments and up to four (4) entry door stations.

These attractive stations conveniently mount right on the wall and are only 0.59" deep! Due to its advanced design the ART1/G2 features oversized buttons for call answering and door release, as well as 'braille' type dot indicators for Talk and Door release functions, for visually impaired individuals.

#### FEATURES

- Oversized front button controls for call answering (voice) and door release
- Uses simple 2-conductor non-polarized (loop) wiring
- Up to four (4) stations can be called from a single call button
- Easy Installation (optional desk mounting using SOB-UNI desk adapter)
- Rugged and Reliable. Simple to Operate
- Low profile surface monitor protrudes only 0.59" from wall
- Adjustable communication and ring tone volumes
- Sound Repeater Output
- Braille type dots for Talk and Door release functions for visually impaired
- Easy station programming using DIP switches
- Selectable Ring Tones
- Can be inter-mixed on the same system with the ART4 Series, ART7 Series monitors and the T-ART/G2 audio only handset stations, and/or other G2+ stations when used with the EL632/G2SE camera speaker/microphone module.

#### SPECIFICATIONS

<b>Dimensions:</b>	All ART1/G2 stations are 3.50"W (89mm) x 5.43"H (138mm) x 0.59"D (15mm). All dimensions shown are outside dimensions for the portion of the station protruding off of the finished wall.
--------------------	--

#### GB2 WIRING INFORMATION

The G2+ system uses simple 2-conductor non-polarized wiring making it ideal for new installations as well as for retrofit applications. All audio, video and data functions are fully digital and using the RAP-GTWIN/HF 100M (or equivalent) cable you can run up to 160 meters from the entrance panel to the furthest monitor.

---

**Alpha Communications**

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599  
TOLL-FREE: (800) 666-4800 • Web: [www.alphacommunications.com](http://www.alphacommunications.com) • Email: [info@alphacommunications.com](mailto:info@alphacommunications.com)

Copyright© 1998-2023 Alpha Communications® - All Rights Reserved.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.