

## Pole mount for DWC-XPZA cameras

DWC-XPZAPLM



### WHAT'S IN THE BOX

5 x Wall Mount Screws, M8 x 30

1 x L Wrench (6.0mm) (for Wall Mount Screws)

2 x Stainless Steel Band 116~140mm

1x Quick Setup Guide

**NOTE:** Download all your support materials and tools in one place.

1. Go to: <http://www.digital-watchdog.com/resources>
2. Search your product by entering the part number in the '**Search by Product**' search bar. Results for applicable part numbers will populate automatically based on the part number you enter.
3. Click '**Search**'. All supported materials, including manuals and quick start guide (QSGs) will appear in the results.



## INSTALLATION

- 1 Position the pole-mount in the desired location on the pole. The pole's max width should be no more than 650mm (the max length of the steel band).
- 2 Attach the mount firmly to the pole using the two (2) steel bands included.
- 3 Starting from the point where the pole-mount bracket will be attached, measure the circumference of the pole. Some poles will taper with their height, so if the pole is tapered, be sure to adapt the band lengths to fit.
- 4 Feed the included steel bands through the slots in the pole bracket.
- 5 Tighten the clamp on the steel band using a Phillips screwdriver (not included). When the clamp is tightened, check that the end of the band is held in place against the pole.
- 6 Bend the band and the clamp to a 90° angle to secure the free end of the remaining length of metal band.
- 7 Use the four (4) M8x30 screws included to secure the camera's wall mount and camera on the pole mount.

