



E-144NC Emergency Call Pull Switch (Momentary)



Architects' And Engineers' Specifications

The Emergency Pull station(s) shall be Alpha Communications® / Cornell **E-144NC**, or approved equal with momentary pull cord operated switch, mounted on a durable Stainless Steel faceplate marked "EMERGENCY", permanently silk-screened onto the faceplate.

Unit shall mount on single-gang electric "gem" box or plaster ring. Unit shall feature a 'Momentary' Normally-Closed switch that opens when the six (6) foot nylon cord is pulled. Unit shall have pigtail wire connectors.

The Emergency Call switch may be used with 'stand-alone' emergency systems, or the **DS100** series annunciator(s).

Contractor shall observe all local and national electrical and building codes.

E-144NC Emergency Call Pull Switch (Momentary)

The Alpha Communications® / Cornell **E-144NC** Emergency Pull station is used to initiate a system 'Emergency' signal. It may be used independently or connected with other call stations and/or intercom stations. The **E-144NC** has a spring loaded Normally-Closed switch that opens in a 'Momentary' fashion, only as long as the pull cord is pulled.

Placing a call is accomplished by pulling on the pull cord. This type of 'Momentary' is usually canceled except at the master annunciator station(s). The **E-144NC** station features a rugged stainless steel faceplate, with the word 'EMERGENCY' permanently silk-screened onto the faceplate.

Features

- 'Momentary' Normally-Closed Pull Cord Activation
- Built-in Pull Cord and Pendant
- Rugged Stainless Steel Faceplate

Specifications

Dimensions:	Height: 4.50" (114mm) Width: 2.75" (69mm) Depth: 1.75" (45mm) into wall Projects: 0.50" (13mm) from mounting surface
Mounting:	Steel City #52171 box with Steel City #52C14 plaster ring, or Alpha Communications® Model IH358 box with IH357 ring, or EXACT EQUAL. Vertical mount.
Connections:	Pigtail Connections

Alpha Communications

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599
TOLL-FREE: (800) 666-4800 • Web: AlphaCommunications.com • Email: info@alphacommunications.com

Copyright© 1998-2016 Alpha Communications® - All Rights Reserved.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.