

STI REX PLUS®



ED-50

PRODUCT OVERVIEW

In addition to the sound of a ferocious attack dog, Rex Plus offers the sounds of the rainforest. Choose the sound that suits you best: the continual sounds of the rainforest, or the option that allows you to use the rainforest sounds as an annunciator; the angry barking dog (for 15-20 seconds) followed by the sound of a siren or the angry barking dog that gets louder and more frequent as the intruder gets closer. Rex Plus is versatile and provides an excellent way to deter burglars, without the annoying problems of owning a real dog. With his electronic radar eyes, Rex Plus can "see" through thick doors, walls and glass. Once his cord is plugged into any standard 110 VAC electrical outlet, he'll stay on duty around the clock.

HOW IT WORKS

Any indoor location can be selected where you wish to detect movement; such as hidden behind the front door. Turn Rex Plus on and he begins detecting. When he detects movement (in attack dog mode), he begins to emit the ferocious barking sounds of a large, unhappy attack dog. The closer the intruder gets, the more frequent the barking becomes. As the intruder backs off, the barking decreases in frequency, stopping completely when movement is out of range. It's very realistic and very effective. There's also a variable volume control that enables the owner to adjust it to meet his or her individual needs.

KEY FEATURES

General Information

- Very realistic - barking gets more frequent as intruder gets closer.
- Switches from the watchdog to the tranquil sounds of nature with the simple slide of a switch.
- Senses movement through walls, doors and glass.
- Variable distance sensitivity (up to 30') as well as volume control.
- Limited 90 day warranty.

Installation

- No installation required.

Electronics

- Plugs into standard 110 VAC electrical outlet.

Options

Your choice of four sounds:

- Continuous sound of the rainforest.
- Barking sound of a ferocious attack dog.
- Sounds of the rainforest to announce the arrival of visitors.
- Barking dog for 15-20 seconds, then siren.

STI Rex Plus®

Dimensions and Technical Information

MODEL AVAILABLE

ED-50 Rex Plus Unit

WARRANTY

Limited 90 day warranty.

Accessory

KIT-ED-50T Additional 12VDC, 100 mA Power Supply

Specifications

Rex Plus consumes a minimal amount of electricity when he's in his "detecting" mode, but uses more power when barking.

Power Supply 12 VDC, 100 mA


Frequency 2.4 GHZ

Net Weight 2.2 lbs.(1.0 KG)


Detection Efficiency

Rex Plus' radar waves can detect intruders through a wide variety of materials with varying levels of efficiency. The following will serve as a guide.

Material	Effect On Range
Glass	Slight reduction
Wooden Doors	Slight reduction
Plaster Walls	Medium reduction
Metal	Heavy reduction
Curtains or Drapes	Slight reduction
Fiberglass or Plastic	No reduction
Paper Cartons	Slight reduction



FRONT VIEW



SIDE VIEW



**Safety Technology
International**

2306 Airport Road info@sti-usa.com
Waterford, MI www.sti-global.com
48327, USA Tel:248-673-9898

Taylor House
34 Sherwood Rd., Bromsgrove,
Worcs., B60 3DR, England

info@sti-emea.com
www.sti-global.com
Tel: +44 (0) 1527 520 999

Unit 7A Lockheed Avenue
Airport Business Park
Waterford X91 HWF2 Ireland