

Product data sheet

Characteristics

AP7301

Rack PDU, Basic, 30A, 200-240V, (14)C13 & (2)C19



Overview

Lead time	Special Order - Call for Quoted Lead Times
-----------	--

Main

Colour	Black
Product or component type	PDU
PDU type	Basic
Cord length	3.00 m
Provided equipment	Installation guide Mounting hardware Toolless mounting kit

Complementary

Input Voltage	200 V 208 V 230 V
Height	60 cm
Width	4.3 cm
Output Voltage	200 V 208 V
Depth	4.5 cm
Net weight	2.72 kg
Mounting location	Front
Mounting preference	No preference
Input Plug Type	NEMA L6-30P
Mounting mode	Rack-mounted
Network frequency	50/60 Hz
Outlet type and quantity	14 IEC 60320 C13 2 IEC 60320 C19

Environment

Product certifications	PSE[RETURN]UL listed
------------------------	----------------------

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.490 cm
Package 1 Width	4.290 cm
Package 1 Length	59.995 cm
Package 1 Weight	2.716 kg

Offer Sustainability

Sustainable offer status	Green Premium product
REACH Regulation	REACH Declaration
EU RoHS Directive	Compliant EU RoHS Declaration
Lead free	Yes
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End Of Life Information
Optimized Energy Efficiency	Energy efficient product
Take-back	Take-back program available

Contractual warranty

Warranty	2 years repair or replace
----------	---------------------------